



T-847-APIR-A/T-857-APIR-A

Motion Sensor Camera (Active)



-Features-

- Sony Super HAD CCD
- Built-in Cone Lens
- Built-in PIR Sensor for Motion Detection
- Relay Control Output

T-847-APIR-A/T-857-APIR-A

Image Sensor	1/3" Sony Super HAD CCD
Resolution	420 TVL / 520 TVL
Illumination	0.2 Lux / F 2.0
S/N Ratio	More than 48dB
Electronic Shutter	1/60 ~ 1/100,000
Gamma	0.45
Lens	3.7mm
White Balance	Auto
Gain Control	Auto
Sync System	Internal
Video Output	1 Vp-p / 75 Ohms
PIR Sensor	Yes (built in)
PIR Relay Output	AC125V / 1A, DC30V / 2A
PIR Relay Alarm Time	2-4 sec (Adjustable)
PIR Detection Angle	H 100° / V 45°
PIR Max Detection Range	30ft
Power	12V DC
Power Consumption	2.9W max.
Operating Temp	14° ~ 122° F (-10° ~ 50° C)