

## ● DDNS SETUP

1. Access the DVR's "System" menu, then "Information"



2. Make a note of the "Webcode"



3. Go to "http://www.ddnsip.net". Enter the "Webcode" and a domain name of your DVR, then press the "Register" button. You will receive a "Registration Success" message if your DVR was registered. Please note that the domain name must be unique to our DDNS server.

The screenshot shows the 'Host Name Service' registration form. It has two input fields: 'Web Code(DDNS ID)' and 'Your domain name'. The domain name field is pre-filled with 'http://' and followed by a blank space and '.ddnsip.net'. There are 'Register' and 'Done' buttons at the bottom.

← Enter "Webcode" and DVR's "Domain Name"

It can take up to thirty (30) minutes for the registration process.

Access your DVR via Internet Explorer:

"DVR DOMAIN NAME".DDNSIP.NET

Make sure all port forwarding rules have been set on your firewall.

**YOU MUST SPECIFY THE WEBSERVER PORT IF CHANGED UNDER THE DVR SETTINGS!**